

**SEMICONDUCTOR MODULE WITH  
SERIAL BUS CONNECTION TO MULTIPLE DIES**

This application is a continuation-in-part of U.S. serial no. 09/564,064 filed on May 3, 2000 entitled "Semiconductor Module with Imbedded Heat Spreader".

**TECHNICAL FIELD**

5       The present invention relates generally to semiconductor modules and in particular to a semiconductor module that allows for more efficient interconnection between the semiconductor module and a computing device's transmission channel.

**BACKGROUND OF THE INVENTION**

10       The semiconductor industry is constantly producing smaller and more complex semiconductors, sometimes called integrated circuits or chips. This trend has brought about the need for smaller chip packages with smaller footprints, higher lead counts, and better electrical and thermal performance, while at the same time meeting accepted reliability standards.

15       In recent years a number of microelectronic packages have been produced to meet the need for smaller chip packaging. One such package is referred to as a chip scale package (CSP). CSPs are so called because the total package size is similar or not much larger than the size of the chip itself. Typically, the CSP size is between 1 and 1.2 times the perimeter size of the chip, or 1.5 times the area of the die. One  
20       example of a CSP is a product developed by TESSERA® called "MICRO BGA" or  $\mu$ BGA. In a CSP, the semiconductor has a set of bond pads distributed across its surface. A first surface of an insulating, flexible film is positioned over the semiconductor surface. Interconnect circuitry is positioned within the film. Electrical

connections are made between the interconnect circuitry and the semiconductor bond pads. Solder balls are subsequently attached to a second surface of the film in such a manner as to establish selective connections with the interconnect circuitry. The solder balls may then be attached to a printed circuit board.

- 5 CSPs may be used in connection with memory chips. Memory chips may be grouped to form in-line memory modules. In-line memory modules are surface mounted memory chips positioned on a circuit board.

As memory demands increase, so does the need for increased memory capacity of in-line memory modules. A need has also arisen for materials and methods that  
10 lead to increased performance by more closely matching the coefficient of thermal expansion of the materials used in these memory modules. Examples of such in-line memory modules are single in line memory modules or SIMMs and dual in-line memory modules or DIMMs. DIMMs have begun to replace SIMMs as the compact circuit boards of preference and essentially comprise a SIMM wherein memory chips  
15 are surface mounted to opposite sides of the circuit board with connectors on each side.

A problem with in-line memory modules is that adding more chips to the circuit board spreads out the placement of the chips on the circuit card and therefore requires reconfiguration of the circuit card connectors and their associated  
20 connections on the motherboard, which means replacing the memory card and in some cases the motherboard.

Another problem with current in-line memory modules is that a separate heat spreader must be positioned across a set of memory chips. The heat spreader adds cost to the assembly process and adds significant weight to the module.

- 25 Existing Multi-Chip Modules (MCM's) typically connect the transmission channel to semiconductors via electrical contact points or ball-outs on the MCM. Each electrical contact point then connects to a semiconductor in the MCM via an electrical lead, so that a signal may be transmitted along the transmission channel to each semiconductor via that semiconductor's electrical lead. However, each  
30 successive electrical lead slightly degrades the signal, by placing a load on the signal.

By the time the signal reaches the last semiconductor connected to a transmission channel, the signal may have degraded so as to be unusable.

Modern MCM's, such as those disclosed in the U.S. patent application number 09/564,064, disclose MCMs that include relatively long electrical leads. The longer  
5 the electrical lead, the more the signal degradation. This is because the speed of the signal is inversely related to the length of the electrical lead. Therefore, existing MCMs can only handle a maximum of approximately thirty two semiconductors connected to a single transmission channel before the signal has degraded to an unusable form.

10 In view of the foregoing it would be highly desirable to provide a semiconductor module that overcomes the shortcomings of the abovementioned prior art devices.

### SUMMARY OF THE INVENTION

15 A semiconductor module is provided which includes a heat spreader, at least two semiconductors thermally coupled to the heat spreader, and a plurality of electrically conductive leads electrically connected to the semiconductors. At least one of the electrically conductive leads is common to both of the semiconductors. The semiconductor module also includes a termination resistor electrically coupled to at  
20 least one of the semiconductors.

A method of making a semiconductor module is also taught, whereby a plurality of electrically conductive leads are provided. At least two semiconductors are electrically coupled to the plurality of electrically conductive leads, where at least one of the electrically conductive leads is common to both of the semiconductors.  
25 The semiconductors are then thermally coupled to a heat spreader. Subsequently, a termination resistor is electrically coupled to at least one of the semiconductors.

The termination resistor coupled to the semiconductors substantially reduces any degradation of the signal caused by a load placed on the signal from electrical leads, as the signal is not being split as is the case with stubs in existing  
30 semiconductor modules. Furthermore, by incorporating the termination resistor into the semiconductor module, the need for a termination resistor on the printed circuit

board is eliminated, thereby reducing the need for additional circuit board space, and decreasing circuit board layout complexity and cost.

### BRIEF DESCRIPTION OF THE DRAWINGS

5 For a better understanding of the nature and objects of the invention, reference should be made to the following detailed description taken in conjunction with the accompanying drawings, in which:

FIG. 1 is a front view of a semiconductor module according to an embodiment of the invention;

10 FIG. 2 is a side view of the semiconductor module shown in FIG. 1;

FIG. 3 is an underside view of the semiconductor module shown in FIG. 1;

FIG. 4 is a side view of a semiconductor module according to another embodiment of the invention;

15 FIG. 5 is a side view of a semiconductor module according to yet another embodiment of the invention;

FIG. 6 is a side view of a semiconductor module according to still another embodiment of the invention;

FIG. 7 is a front view of a semiconductor module according to another embodiment of the invention;

20 FIG. 8 is a front view of a semiconductor module according to yet another embodiment of the invention;

FIG. 9 is a perspective view of multiple semiconductor modules installed on a printed circuit board;

25 FIG. 10 is a side view of a semiconductor module according to another embodiment of the invention;

FIG. 11 is a flow chart of a method of making a semiconductor module according to an embodiment of the invention;

FIG. 12 is a side view of a semiconductor module according to yet another embodiment of the invention;

30 FIG. 13 is a front view of a semiconductor module according to a further embodiment of the invention;

FIG. 14 is a side view of the semiconductor module shown in FIG. 13; and  
FIG. 15 is a flow chart of a method of making a semiconductor module  
according to another embodiment of the invention.

Like reference numerals refer to corresponding parts throughout the several  
5 views of the drawings.

### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

FIG. 1 is a front view of a semiconductor module 100 according to an  
embodiment of the invention. A semiconductor 102 is electrically connected to a  
10 plurality of traces or electrically conductive leads 108 by any conventional method  
such as wire bonding or thermocompression bonding. The electrically conductive  
leads 108 may be incorporated into flexible circuitry or tape 104, which preferably  
consists of copper traces within a thin dielectric substrate (such as polyimide, epoxy,  
etc.).

15 As shown in FIG. 1, the flexible circuitry 104 may be bonded, with an epoxy  
or the like, directly onto the side of the heat spreader 106. The heat spreader 106 is  
preferably made from a material with good heat dissipation properties, such as a  
metal.

In a preferred embodiment, two semiconductors 102 are positioned on  
20 opposing sides of the heat spreader 106. The leads 108 preferably run the length of  
each sides of the heat spreader 106, culminating at electrical contact points 110 at the  
base of the heat spreader 106. Electrical contact points 110 may for example  
comprise solder balls or bond pads. The semiconductors may further comprise of  
single dies or multiple stacked dies.

25 FIG. 2 is a side view of the semiconductor module 200 shown in FIG. 1. This  
view shows the semiconductors 102 and the flexible circuit 104 attached to both sides  
of the heat spreader 106. As can be seen, the flexible circuit 104 wraps around the  
sides walls 202 and 204 and base 206 of the heat spreader 106.

FIG. 3 is an underside view of the semiconductor module shown in FIG.1.  
30 This figure more clearly shows the array of electrical contact points 110. Each lead  
108 connects a semiconductor 102 to a distinct contact point 110. However, certain

2020071298-020702

of the contact points **112** are common to both semiconductors **102**. In this case, a single lead **108** connects both semiconductors **102** to a shared common contact point **112**. Common contact points **112** may include a common voltage supply node , a reference voltage node, or an electrical ground node. Shared contact points **112** .

5 reduce the overall number of leads **108** and contact points **110** needed and therefore reduces the footprint of the module. The contact points **110** may be implemented as solder bumps or balls, metal points, or any other electrical connection. An advantage of placing the contact points at the base of the heat spreader **106** is that the contact points **110**, being remote from the semiconductor **102**, do not experience major

10 temperature variations and therefore have reduced thermal mismatch stress. Thermal mismatch stress is caused by the low thermal expansion of the semiconductor **102** relative to the typically much higher expansion of a printed circuit board.

FIG. 4 is a side view of a semiconductor module **400** according to another embodiment of the invention. In this embodiment, semiconductors **402** on a flexible circuit **404**, are bonded directly to a heat spreader **406**. The bond may be by any

15 means but is preferably made by gluing the semiconductors **402**, with an epoxy or the like, to the side of the heat spreader **406**. The glue is chosen to closely match the thermal expansion properties of the semiconductor **402**, heat spreader **406** and flexible circuit **404**. The glue should also have good thermal conduction properties. This

20 embodiment, where the semiconductors **402** are bonded directly to the heat spreader, **406** is favored due to the direct conduction of heat from the semiconductors **402** to the heat spreader **406**.

FIG. 5 is a side view of a semiconductor module **500** according to yet another embodiment of the invention. In this embodiment, the heat spreader **506** has a “u”

25 shape defining a channel **508** . This embodiment provides the benefit of increasing the surface area of the heat spreader **506** exposed to the surrounding air, thus increasing the rate that heat generated by the semiconductors **502** is dissipated to the surrounding air. Either the heat spreader **506** may conform to the shape of the flexible circuit **504** and semiconductor **502**, or the flexible circuit **504** and semiconductor **502**

30 may conform to the shape of the heat spreader **506**. Both of these configurations are shown in FIG. 5, at **510** and **512** respectively.

FIG. 6 is a side view of a semiconductor module **600** according to still another embodiment of the invention. In this embodiment, the heat spreader **606** is in a “n” shape forming an interior channel **608**. This embodiment also provides the benefit of increasing the surface area of the heat spreader **606** exposed to the surrounding air, thus increasing the rate heat generated by the semiconductors **602** is dissipated to the surrounding air. In this embodiment, the heat dissipating external surfaces may further dissipate heat by being exposed to an external air circulation device (e.g. a fan).

In the embodiments shown in FIGS. 1 to 5, signal channels in an electronic device may enter and exit the semiconductor module at electrical contact points in one area or footprint at the base of the heat spreader, as shown at **110** of FIG. 1. In the embodiment shown in FIG. 6, however, signal channels in an electronic device enter the semiconductor module **600** at electrical contact points **610** and exit from electrical contact points **612**.

FIG. 7 is a side view of a semiconductor module **700** according to another embodiment of the invention. In this embodiment, leads **708** fan out on the flexible circuitry **704**. That is, the leads **708** in the flexible circuitry **704** are closer together at the semiconductor **702** than at the array **710**, which is more spread out than that shown in FIG. 1. The fanned out leads **708** create a more dispersed array with contact points **710** spaced further from one another. This embodiment compensates for a constant size footprint should larger semiconductors **702** be incorporated into the module at a later stage.

FIG. 8 is a side view of a semiconductor module **800** according to yet another embodiment of the invention. In this embodiment, two tape and semiconductor combinations **802** and **804** are placed on one heat spreader **806**. Thus, the apparatus of FIG. 8 processes two or more separate signal channels with a single heat spreader **806**.

FIG. 9 is a perspective view **900** of multiple semiconductor modules **908** installed on a printed circuit board (PCB). The semiconductor modules **908** may be placed directly onto channels **902** on a PCB **910** or other suitable substrate, such that each electrical contact point electrically connects with a channel **902**.

The semiconductor modules **908** may be placed directly onto a PCB **910**, such as a motherboard, or alternatively onto an in-line memory module circuit card which in turn slots into another PCB, such as a motherboard. In this manner the footprint of an in-line memory module circuit card may remain constant even if additional

5 semiconductor modules **908** are slotted onto the in-line memory module circuit card. As the footprint of the array is always constant, the in-line memory module circuit card does not have to be changed each time additional memory is required, thereby enhancing the upgradability of electronic devices. The invention provides a memory module with a small footprint. Adding further chips to the module does not effect the

10 footprint.

When in an aligned position, each electrical contact point electrically connects with a corresponding electrical contact on the substrate or PCB. Where the electrical contact points are solder bumps, the electrical connection between the semiconductor module and the PCB may be made by heating the solder bumps to cause reflow of the

15 solder and allowing subsequent cooling, thereby fusing the semiconductor module **908** to the PCB **910**.

Alternatively, or in addition, fastening mechanisms **904** and **906** may be provided for securely anchoring the semiconductor modules **908** onto the PCB **910**. Such fastening mechanisms **904** and **906** may include clamps, slots, or the like.

20 FIG. 10 is a side view of a semiconductor module **1000** according to another embodiment of the invention. In this embodiment the semiconductor module **1000** connects to a pin grid array (PGA) socket or slot **1002**, which in turn connects to a PCB. This embodiment is especially useful when connecting a semiconductor module to PCB's with incompatible footprints. In this way, a semiconductor module

25 **1000** with a footprint created by electrical contact points **110**, may be connected to a PCB with a different footprint, where electrical contacts **1004** on the PGA slot **1002** are arranged to correspond with the footprint on the PCB.

FIG. 11 is a flow chart of a method **1100** of making a semiconductor module according to an embodiment of the invention. A plurality of electrically conductive

30 leads are provided **1102**, preferably on a flexible circuit or tape. Two semiconductors are then electrically connected **1104** to the leads. The semiconductors are then



2020071298-020702

thermally coupled 1106 to a heat spreader. This is preferably done by mounting 1108 the semiconductor directly to opposing walls of the heat spreader as shown in FIGS. 4-6. Alternately, the flexible tape may be used as the contact surface with the heat spreader as shown in FIG. 2. The leads may then be soldered 1110 to a PCB. The  
5 module may also be anchored 1112 to the PCB by means of a fastening mechanism as discussed above. Alternatively, the module may connect 1114 to a PGA as described in relation to FIG. 10. Anchoring 1112, soldering 1110, and connecting 1114 may occur simultaneously.

In an alternative embodiment, a semiconductor package such as a CSP may  
10 have its solder balls attached to the flexible circuitry. The combination of the semiconductor package and the flexible circuitry is then bonded to the heat spreader. In this manner existing semiconductor packages may be used to manufacture the semiconductor module according to the invention.

Another alternative embodiment may include shielding to protect the  
15 semiconductor from electromagnetic forces. In addition, adhesive may be placed between the tape and the base of the heat spreader to cushion the contact points and ensure contact between the contact points and the PCB.

The semiconductor module of the invention eliminates the need for a separate heat spreader. The invention reduces overall cost and weight through shared common  
20 contact points or nodes. The common contact points also allow for a constant footprint to be maintained independent of the size or number of semiconductors used. Furthermore, the module is reliable as the semiconductors are not exposed to as high thermal stresses. The module also substantially improves heat dissipation by exposing greater surface areas to the surrounding air.

25

### Multi-Chip Modules

As explained above in the background section of this specification, many existing semiconductor modules position their embedded semiconductors relatively far from the circuit board to which they are attached. Each semiconductor in such  
30 semiconductor modules connects to a transmission channel via its own electrical lead. A signal passing along the transmission channel from lead to lead is degraded by a

load placed on the signal by each successive lead. The longer the stub, the more the signal is degraded. Each successive lead further degrades the signal, until such time as the signal has been degraded so as to be useless. Most semiconductor modules also include a termination resistor at the end of each transmission channel on the printed circuit board. The present invention addresses the problem associated with signal degradation in semiconductor modules having relatively long electrical leads.

Impedance matching of an electrical load to the impedance of a signal source and the characteristic impedance of a transmission channel is often necessary to reduce reflections by the load, back into the transmission channel. As the length of a non-terminated transmission line increases, reflections become more problematic. When high frequency signals are transmitted or passed through even very short transmission lines, such as printed circuit board (PCB) traces, a termination resistor may be inserted at the load to avoid reflections and degradations in performance.

In the multi-chip modules of the present invention, termination resistors are preferably internal to the MCM's. The use of external termination resistors presents a number of drawbacks. The placement of a termination resistor outside an MCM results in an additional stub or short transmission line between the termination resistor and the integrated circuit device. External termination resistors also require significant circuit board space, and increase circuit board layout complexity and cost.

FIG. 12 shows a side view of a semiconductor module 1200 according to yet another embodiment of the invention. A number of semiconductors 1204 are electrically coupled to a plurality of traces or electrically conductive leads 1202 (only one is shown) by any conventional method such as wire bonding or thermocompression bonding. The electrically conductive leads 1202 are preferably incorporated into a flexible circuit or tape 1210, which preferably consists of copper traces within a thin dielectric substrate (such as polyimide, epoxy, etc.).

The semiconductors 1204 on the flexible circuit 1210, are preferably bonded directly to a heat spreader 1218. Alternatively, as shown and described in relation to FIG. 2, the flexible circuit 1210 may be bonded directly to the heat spreader 1218. The bond may be made by any means but is preferably made by gluing the semiconductors 1204 or flexible circuit 1210, with an epoxy or the like, to the side of

the heat spreader **1218**. The glue is chosen to closely match the thermal expansion properties of the semiconductor **1204**, heat spreader **1218**, and flexible circuit **1210**. The glue should also have good thermal conduction properties. This embodiment, where the semiconductors **1204** are bonded directly to the heat spreader **1218** is  
5 favored due to the direct conduction of heat from the semiconductors **1204** to the heat spreader.

The heat spreader **1218** is preferably made from a material with good heat dissipation properties, such as a metal. In a preferred embodiment, the semiconductors **1204** are positioned on opposing sides of the heat spreader **1218**. The  
10 electrical leads **1202** connect the semiconductors **1204** to electrical contact points **1216** at the base of the semiconductor module **1200**. In use, electrical contact points **1216** may for example comprise solder balls or bond pads. The electrical contact points **1216** electrically couple the electrical leads **1202** to a transmission channel **1214** on a printed circuit board **1212**. Electrical signals are transmitted along the  
15 transmission channel **1214** to electrical contact points **1216**. The electrical signals are then passed from the electrical contact points **1216** through the electrical leads **1202** to each of the semiconductors **1204**.

In this embodiment, the semiconductors **1204**, on opposing sides of the heat spreader **1218**, are connected to one another in series by the electrical lead **1202**. It  
20 should be noted that multiple (i.e., more than two) semiconductors **1204** may be connected together in series. The final semiconductor in the series, remote from the transmission channel, electrically couples to a termination resistor **1208**. The termination resistor **1208** is preferably thermally coupled to the heat spreader **1218** so that any heat built up in termination resistor **1208** can dissipate through the heat  
25 spreader.

The termination resistor **1208** connected in series to the semiconductors **1204** substantially reduces any degradation of the signal caused by a load placed on the signal from the electrical leads **1210**, as the signal is not being split as is the case with stubs in existing semiconductor modules. A signal is transmitted from a signal  
30 source, along the transmission channel **1214**, along an electrical lead **1202**, to each semiconductor **1204** connected in series, and is terminated at the termination resistor

**1208**. Furthermore, by incorporating the termination resistor **1208** into the semiconductor module **1200**, the need for a termination resistor on the printed circuit board **1214** is eliminated.

This embodiment of the invention is particularly useful now that the memory capacity of individual semiconductors has increased to a point where only a few semiconductors are needed for many applications.

FIG. 13 is a front view of the semiconductor module **1300** according to a further embodiment of the invention. This semiconductor module **1300** is identical to the semiconductor module **100** shown in FIG. 1, except for a termination resistor **1302** disposed on the heat spreader. FIG. 14 is a side view of the same semiconductor module **1300** shown in FIG. 13. In this embodiment, the semiconductors **1304** are not connected in series, but rather each semiconductor connects to its own transmission channel. Likewise, each termination resistor **1302** connects to a single semiconductor. In use, a signal is transmitted along each transmission channel, to its respective semiconductor, after which it is terminated at a termination resistor **1402** to eliminate reflections.

The resistance value of the termination resistor **1208** (FIG. 2) or **1302** (FIGS. 13 and 14) is selected such that its impedance substantially matches the impedance of the transmission channel and signal source to which it is connected. Furthermore, any form of termination may be used, such as parallel termination, Thevenin termination, series termination, AC termination, Schottky-diode termination or the like.

FIG. 15 is a flow chart of a method **1500** of making a semiconductor module according to another embodiment of the invention. According to the method **1500** a plurality of electrically conductive leads are provided (step **1502**). At least two semiconductors are electrically coupled (step **1504**) to the plurality of electrically conductive leads, where at least one of the electrically conductive leads is common to both of the semiconductors. The semiconductors are then thermally coupled (step **1506**) to a heat spreader. Subsequently, a termination resistor is electrically coupled (step **1508**) to at least one of the semiconductors.

The semiconductors may be electrically coupled in series, where the semiconductors are capable of being electrically coupled to a transmission channel.

Moreover, an additional termination resistor may be electrically coupled to the semiconductor not already connected to the termination resistor, where each of the semiconductors is capable of being electrically coupled to a separate transmission channel.

- 5           While the foregoing description and drawings represent the preferred embodiments of the present invention, it will be understood that various additions, modifications and substitutions may be made therein without departing from the spirit and scope of the present invention as defined in the accompanying claims. In particular, it will be clear to those skilled in the art that the present invention may be
- 10 embodied in other specific forms, structures, arrangements, proportions, and with other elements, materials, and components, without departing from the spirit or essential characteristics thereof. The presently disclosed embodiments are therefore to be considered in all respects as illustrative and not restrictive, the scope of the invention being indicated by the appended claims, and not limited to the foregoing
- 15 description.

204020 862700T